

Product Name: OpenVox A400P12 - 2 FXO 1 FXS Manufacturer: OpenVox Model Number: A400P12

OpenVox A400P12 - 2 FXO 1 FXS

The OpenVox A400P12 - 2 FXO 1 FXS is an OpenVox A400P bundled with 2 FXO modules and 1 FXS module.

You can also add FXO-100 or FXS-100 modules to use with this product according to your requirements.

The OpenVox A400P12 is designed to be fully compatible with the TDM400P Asterisk Analog Telephony card.

The FXO-100 (FXO) module allows the A400P card to terminate analog telephone lines (POTS). The FXS-100 (FXS) module allows the A400P card to terminate analog telephones. Key Features and benefits:

- · Scalable: Just add additional cards to extend the system.
- Easy to use: Full software and hardware compatible with TDM400P.
- Modular design: Can upgrade at any time by adding extra FXO or FXS modules up to a total of 4 per card. (A400P12 comes with otwo FXO modules and 1 fxs module.)
- Both 3.3v or 5v PCI slots can be used with this card.
- Module Pin to Pin compatible with X100M and S100M. You can use X100M/S100M modules on this card, or use FXO-100/ FXS-100 Modules from OpenVox.
- Excellent value: High quality at a low price.
- Application ready: Use Asterisk to build your IP-PBX system.
- RoHS Compliant.
- Certificates: CE, FCC
- Five year warranty

Technical Specifications

- Up to 4 ports through a combination of FXS and FXO modules
- 4 RJ-11 interfaces on a single PCI bracket
- 32 bit 33MHz PCI and fully PCI 2.2 compliant
- 32 bit bus master DMA data exchanges across PCI interface at 132 Mbytes/sec
- Autosense compatibility with 5 V and 3.3 V PCI busses compatible
- Firmware accelerate I/O access to achieve high stability

Power

• 2.77W Minimum, 11.6W Maximum at 3.3 V or 5 V.

Operation temperature

0°C to 50°C

Storage temperature

-40°C to 125°C

Dimension

• 136.3mm*101mm*16mm

OpenVox A400P12 - 2 FXO 1 FXS

Weight

• 82g

Price: £88.30