

Hướng dẫn cấu hình

FXO Gateway Dinstar kết nối Asterisk

Cấu hình trên asterisk

1. Tạo SIP Trunk Dinstar trên asterisk

Thêm cấu hình sau vào trong file sip.conf

```
[Dinstar]
```

```
disallow=all
```

```
host=x.x.x.
```

```
type=peer
```

```
allow=ulaw
```

```
allow=alaw
```

```
nat=yes
```

```
canreinvite=yes
```

```
qualify=yes
```

```
context=from-trunk
```

```
insecure=port,invite
```

```
dtmfmode=rfc2833
```

2. Cấu hình gọi ra qua Trunk Dinstar

Cấu hình trong file extension.conf

3. Cấu hình nhận cuộc gọi từ Trunk Dinstar

Cấu hình trong file extension.conf

Cấu hình trên Dinstar

1. Tạo IP Trunk (IP – 5060)

IP Trunk Modify	
Index	63
Description	Freeswitch
Remote Address	172.16.0.8
Remote Port	5080
Heartbeat	<input checked="" type="checkbox"/> Enable

2. Tạo port Group

Port Group Modify	
Index	7
Description	fxo
Primary Display Name	
Primary SIP User ID	
Primary Authenticate ID	
Primary Authenticate Password	
Secondary Display Name	
Secondary SIP User ID	
Secondary Authenticate ID	
Secondary Authenticate Password	
Offhook Auto-Dial	12345
Auto-Dial Delay Time	0
Port Select	Cyclic Ascending
Pick Up on Group	*#
Port	<input checked="" type="checkbox"/> Port 0(FXO) <input checked="" type="checkbox"/> Port 1(FXO) <input checked="" type="checkbox"/> Port 2(FXO) <input checked="" type="checkbox"/> Port 3(FXO) <input type="checkbox"/> Port 4(FXS) <input type="checkbox"/> Port 5(FXS) <input type="checkbox"/> Port 6(FXS) <input type="checkbox"/> Port 7(FXS)

3. Định tuyến gọi ra

IP->Tel Routing Modify	
Index	30
Description	sip server
Calls from	<input checked="" type="radio"/> IP Trunk 63 <172.16.0.8> <input type="radio"/> SIP Server
Caller Prefix	any
Callee Prefix	any
Calls to	<input type="radio"/> Port 0 <input checked="" type="radio"/> Port Group 7 <fxo>

4. Định tuyến gọi vào từ PSTN

Tel->IP/Tel Routing Modify	
Index	<input type="text" value="31"/>
Description	<input type="text" value="any"/>
Calls from	<input type="radio"/> Port <input type="text" value="0"/>
	<input checked="" type="radio"/> Port Group <input type="text" value="7 <fxo>"/>
Caller Prefix	<input type="text" value="any"/>
Callee Prefix	<input type="text" value="any"/>
Calls to	<input type="radio"/> Port <input type="text" value="0"/>
	<input type="radio"/> Port Group <input type="text" value="6 <fxs>"/>
	<input checked="" type="radio"/> IP Trunk <input type="text" value="63 <172.16.0.8>"/>
	<input type="radio"/> SIP Server

Mọi yêu cầu hỗ trợ vui liên hệ qua: <http://voip.com.vn>